

Reading-out the state inductively and microwave spectroscopy of an interferometer-type charge qubit

D. Born,¹ V.I. Shnyrkov,^{1,*} W. Krech,^{1,†} Th. Wagner,² E. Il'ichev,² M. Grajcar,^{2,‡} U. Hübner,² and H.-G. Meyer²

¹*Friedrich Schiller University, Institute of Solid State Physics, Helmholtzweg 5, D-07743 Jena, Germany*

²*Institute for Physical High Technology, P.O. Box 100239, D-07702 Jena, Germany*

(Dated: February 2, 2008)

We implemented experimentally an interferometer-type charge qubit consisting of a single-Cooper-pair transistor closed by a superconducting loop that is in flip-chip configuration inductively coupled to a radio frequency tank circuit. The tank permits to readout the qubit state, acting as inductance measuring apparatus. By applying continuous microwave power to the quantum device, we observed inductance alterations caused by redistributions of the energy level populations. From the measured data, we extracted the energy gap between ground and upper levels as a function of the transistor quasicharge as well as the Josephson phase across both junctions.

PACS numbers: 74.50.+r, 85.25.Am, 85.25.Cp

Various quantum properties of superconducting structures with small Josephson tunnel junctions have been experimentally demonstrated by several research groups (see, e.g., Ref. 1 and references herein). The results have been widely discussed in literature because such devices might serve as prototypes for quantum bits (qubits).

In this context, the single-Cooper-pair transistor has attracted renewed attention. The device consists of two mesoscopic Josephson junctions coupled by a small island. The Hamiltonian of this system can be written as²

$$H = E_C(n - n_g)^2 - \varepsilon_J(\delta) \cos \varphi. \quad (1)$$

Here the first term on the r.h.s. is the charging energy of the island whereas the second one describes its Josephson coupling to the leads. The variable $n = 2m$ implies the number m of excess Cooper pairs on the central electrode, the parameter $n_g = C_g V_g / e$ is continuously controllable by the gate voltage V_g via the capacitance C_g . The one-electron Coulomb energy, $E_C = e^2 / 2C_\Sigma$, is expressed through the island's sum capacitance C_Σ . Furthermore, the coupling strength,

$$\varepsilon_J(\delta) = [E_{J1}^2 + E_{J2}^2 + 2E_{J1}E_{J2} \cos \delta]^{1/2}, \quad (2)$$

is a function of the total phase across both junctions, $\delta = \varphi_1 + \varphi_2$ (being here a good quantum variable). $E_{J1, J2}$ are the individual Josephson energies and $\varphi_{1,2}$ the respective junction phases. Note that the observable m is conjugated to the island's phase, $\varphi = (\varphi_2 - \varphi_1) / 2$. In order to realize charge qubits, we designed the system parameters to fulfill the domination, $E_{CP} > \varepsilon_J(\delta)$, of the Cooper pair Coulomb energy, $E_{CP} \equiv 4E_C$, over the coupling strength ε_J .

In earlier studies, microwave induced transitions between ground and upper energy states in single-charge transistors were observed by measuring the switching current^{3,4,5} or by means of the photon-assisted quasiparticle current⁶. Later the quantum coherent oscillations in similar configurations have been detected by making use of microwave-pulsed readouts.^{7,8}

Recently, a new possible solution was theoretically proposed by several authors.^{9,10} The main idea is to enclose a single-Cooper-pair transistor into a superconducting inductive loop forming an interferometer. The advantage of this circuit is its low dissipation and, therefore, the remarkably weak decoherence.¹ For realizing the quantum measuring process, the loop is inductively coupled to a radio frequency tank circuit.

In this paper, we introduce experimentally the conception of an interferometer-type charge qubit in conjunction with a readout procedure managed by measuring the qubit's reverse Josephson inductance,^{10,11}

$$\mathcal{L}_J^{-1} = (2e/\hbar)^2 \cdot \partial^2 H / \partial \delta^2. \quad (3)$$

We put it into practice along the lines of the conventional impedance measuring technique¹² by means of a high-quality tank inductively coupled to the interferometer loop. Based on this method, we present results of the spectroscopic investigation of the quantum device that is manipulated by a microwave field injected via a coaxial cable (UHF line, Fig. 1). These results demonstrate the utility of the used design relating to development and characterization (weak continuous quantum measuring) of future building blocks (coupled qubits) for quantum information circuits as well.

The principle of measurement is as follows: The expectation value $\langle m | \mathcal{L}_J^{-1}(n_g, \delta) | m \rangle$ is determined not only by the quasicharge en_g (controlled by the gate voltage) and the phase δ (controlled by an external magnetic flux Φ_e threading the interferometer loop) but also by the band index m .¹³ Within the two-level approximation, the mean values in the upper state ($m=1$) and in the ground state ($m=0$) have the opposite sign,¹¹ $\langle 1 | \mathcal{L}_J^{-1}(n_g, \delta) | 1 \rangle \simeq -\langle 0 | \mathcal{L}_J^{-1}(n_g, \delta) | 0 \rangle$. Consequently, a change of the band index m results in a relevant impedance change that causes a shift of the tank resonance frequency.

Quantitatively, we consider only the case when the geometrical inductance L_q of the loop is sufficiently small, ensuring in this way a unique relationship between the flux Φ_e and the phase difference δ . This requirement can




FIG. 1: Diagram of the measuring setup including the micrograph of the Al based single-Cooper-pair transistor (closed by the superconducting loop inductance L_q). On the r.h.s, the tank circuit and some further electronic components are shown (cf. text). The phase δ is guaranteed to be a good quantum variable for sufficiently large ground capacitance, $C_0 \gg C_\Sigma$. The angular phase shift α (Eq. 6) between tank voltage detected by the amplifier and current signal I_{rf} is determined by using a lock-in amplifier (not depicted here).

be expressed as follows within the two-band model, ¹¹

$$L_q < 2 \left(\frac{\Phi_0}{2\pi} \right)^2 \frac{\Delta E(n_g = 1, \delta = \pi)}{E_{J1} E_{J2}}, \quad (4)$$

where Φ_0 is the flux quantum and

$$\Delta E = [D^2(n_g) + \varepsilon_J^2(\delta)]^{1/2} \quad (5)$$

is the local band spacing (with $D \equiv E_{CP}(1 - n_g)$). We emphasize the fact that the coupling strength ε_J and, therefore, the gap ΔE can be significantly reduced in the vicinity of the operating point $n_g=1$, $\delta=\pi$ even for relatively large ratios $E_{J1,J2}/E_C$.

As discussed above, the observable $\mathcal{L}_J^{-1}$ takes different expectation values for the energy bands $m=0$ and $m=1$. Therefore, a redistribution of the level populations caused by microwave excitations (in competition with relaxation processes) results in a change of the quantum-statistical mean value $\langle \mathcal{L}_J^{-1} \rangle$. In order to prove this effect, the loop was coupled through a mutual inductance $M = k\sqrt{L_q L_T}$ (where $k \ll 1$ is the coupling coefficient) to the tank circuit (with known inductance L_T and quality factor Q). The tank is driven by an rf current I_{rf} at a frequency ω close to its resonance frequency ω_T . This current generates an rf flux Φ_{rf} threading the interferometer ring. Provided that, first, this rf flux is small, $\Phi_{rf} \ll \Phi_0$, and, second, the condition $L_q |\langle \mathcal{L}_J^{-1} \rangle| \ll 1$ is fulfilled, variations of the interferometer inductance can be described by making use of the formula¹⁴

$$\tan \alpha \simeq k^2 Q L_q \langle \mathcal{L}_J^{-1} \rangle, \quad (6)$$

where α is the phase shift between drive current I_{rf} and tank voltage U_T to be measured.




FIG. 2: Tank phase shift α vs. gate parameter n_g without microwave power (lowest curve) and with microwave power at different excitation frequencies. The data correspond to $\omega_{UHF}/2\pi = 8.9, 7.5, 6.0$ GHz (from top to bottom). The magnetic flux $\Phi_e = \Phi_0/2$ threading the interferometer loop provides a total phase difference $\delta = \pi$ across the single-Cooper-pair transistor. (For clarity, the upper curves are shifted.)

The used measurement setup is shown in Fig. 1. The Nb square-shaped pancake tank coil ($L_T \simeq 170$ nH) was fabricated lithographically on an oxidized Si substrate. An external capacitance C_T is used to complete the resonance circuit. This high-quality tank ($Q \simeq 700$) is biased by the rf current I_{rf} at the resonance frequency of $\omega_T/2\pi \simeq 28$ MHz. The rf voltage U_T across the tank circuit was measured by means of a sequence of cold and room temperature amplifiers. The angular phase shift α was determined using an rf lock-in voltmeter.

The qubit under investigation is placed in the middle of the coil in flip-chip configuration. The transistor was fabricated out of Al by the conventional shadow evaporation technique. The transistor's gate line is filtered by means of three copper powder filters (with a total length of about 35 cm) at the temperatures 2 K, 50 mK and 10 mK. The attenuation of this line is about 120 dB at 5 GHz and 300 dB at 20 GHz. Microwave irradiation for photon-assisted excitations of the quantum device is fed into the sample via an UHF line consisting of a commercial coaxial cable from room temperature to ~ 2 K as well as via a resistive coaxial cable (known as Thermo-Coax) from ~ 2 K to 10 mK. In order to reduce external interferences, two 20 dB commercial attenuators were installed at the temperature levels 2 K and 10 mK. The external magnetic flux Φ_e applied to the interferometer loop is produced by a dc current I_{dc} through the tank coil. In order to feed both currents I_{dc} and I_{rf} into the tank, a simple bias tee is used (see Fig. 1).

The angular phase shift α (6) was measured as a function of the gate voltage as well as of the dc current in the tank coil that generates the external flux Φ_e . The coupling coefficient between tank and superconducting loop was obtained experimentally¹⁴ to be $k = 0.026$. The mutual inductance is $M = 0.42$ nH, and the geometri-




FIG. 3: Energy gap ΔE between the ground and upper bands of the transistor determined from the experimental data for the case $\delta=\pi$. (Some examples of these data are shown in Fig. 2.) Dots represent the experimental data, the solid line corresponds to the fit within the two-band model (cf. text).

cal loop inductance was calculated to be $L_q = 1.5$ nH. Suitable adjusting the tank drive current I_{rf} permitted the qubit operation in the required small-signal limit, $\Phi_{rf} \sim 10^{-3}\Phi_0$. The layout size of the junctions is $140\text{ nm} \times 180\text{ nm}$. Deviations from these nominal dimensions in the order of 10 % (caused by the fabrication process) were estimated by means of the micrograph of the real structure. In accordance with this fact, the spectroscopically determined Josephson coupling energies showed a certain difference, $|E_{J1} - E_{J2}| \approx 5$ GHz (see below). The measurements were performed in a dilution refrigerator at a nominal temperature of about 10 mK inside magnetic and superconducting shields.

In a first set of experiments, we investigated charging effects in the interferometer. Adjusting the external flux ($\Phi_e = \Phi_0/2$), we fixed the phase ($\delta = \pi$) and measured the dependence of the statistical average $\langle \mathcal{L}_J^{-1} \rangle$ (or α , cf. Eq. 6) on the parameter n_g . This dependence turned out to be rather weak due to the large ratio between Josephson and charging energies. Nevertheless, the coupling strength could be reduced down to $\varepsilon_J(\delta = \pi) \approx 5$ GHz. Therefore, a variation of $\langle \mathcal{L}_J^{-1} \rangle$ with n_g was actually measurable for operating values of δ in the vicinity of π . Indeed, the 2e-periodic oscillations of $\langle \mathcal{L}_J^{-1} \rangle$ or α with respect to the gate charge $en_g = C_g V_g$, explicitly demonstrating its quasicharge character, are clearly seen in Fig. 2 (bottom curve).¹⁵

Small-amplitude continuous microwave irradiation of the sample varied significantly the obtained dependence: Now distinguished peaks appeared in the $\alpha(n_g)$ characteristics (upper curves in Fig. 2). Their positions depend on the frequency ω_{UHF} . Increasing microwave amplitudes led to a slight change of the peak width only. Thus we demonstrated that the peaks are originated by resonant excitations of the system from ground to up-




FIG. 4: Dependence of the phase shift α on the two parameters n_g and Φ_e . The qubit is illuminated by a microwave with the frequency of 8.0 GHz. The periodic circular structure demonstrates the variation of the total interferometer-tank impedance due to transitions from the lower to the upper energy band. Especially, the “crater ridges” correspond to all combinations of the parameters n_g and Φ_e that give the same energy gap between the respective states equal to 8.0 GHz.

per states. (In general, the measured peaks disappeared at higher temperatures corresponding to the used frequency. For instance, for a peak induced by the frequency $\omega_{UHF}/2\pi = 8$ GHz, this temperature is about $T \simeq 400$ mK.) The microwave-induced transitions (at fixed parameters ω_{UHF} and δ) from the ground to the upper states should correspond to specific values n_g . Following this consideration and extracting the peak positions from the α - n_g curves measured at different microwave frequencies, we depicted the energy differences $\Delta E = \hbar\omega_{UHF}/2\pi$ between ground and upper levels as a function of n_g (Fig. 3). Then we fitted the spectroscopic data (analogously as reported in Ref. 8) by making use of the band gap (5) within the two-level approximation, providing $\varepsilon_J(\delta = \pi) = 4.4$ GHz and $E_C = 2.2$ GHz. (A fitting procedure by making use of a numerical treatment of the complete Hamiltonian (1) delivers practically the same values.)

In further experiments, we measured the phase shift α as a function of the applied magnetic flux Φ_e in the vicinity of $\Phi_0/2$ at varying gate voltage V_g . At the same time, the microwave frequency was fixed. This way we obtained a spatial representation of the microwave-induced transitions as a function of both parameters n_g and Φ_e . The results for the microwave frequency of 8 GHz are presented in Fig. 4. Finally fitting the ring-shaped “crater rim” by means of the band spacing Eq. 5, we found spectroscopic data $E_{J1} = 70.0$ GHz and $E_{J2} = 74.4$ GHz for the junctions’ Josephson energies (cf. Fig. 5).

In conclusion, we have successfully implemented an alternative quantum two-level system in a superconduct-




FIG. 5: Top view of the $\alpha(n_g, \Phi_e)$ mountain range of Fig. 4. Here the white ring approximates the ridge of the central crater leading to the fit $E_C = 2.2$ GHz, $E_{J1} = 70.0$ GHz, and $E_{J2} = 74.4$ GHz within the two-level model.

ing circuit with readout. In this connection, we demonstrated the suitability of the Josephson quantum inductance term for developing a readout procedure. We performed a microwave spectroscopy of an interferometer-type charge qubit, making use of an rf tank readout. We reconstructed the energy gap between lower and upper energy levels as a function of the gate charge at fixed phase across the double junction. We demonstrated experimentally that the energy gap can be varied by changing both gate charge and external flux threading the interferometer loop. In view of the relatively large ratio E_J/E_C , effects accompanied with the change of the gate charge were observed in the vicinity of $\delta=\pi$ only. Our results indicate that the investigated qubit device is a potential candidate for realizing solid-state quantum processing in conjunction with weak characterization.

We thank A. Smirnov, A. Zagoskin, and A. Zaikin for fruitful discussions. We also would like to thank A.N. Omelyanchouk for comments and H. Mühlig for technical assistance. This work was partially supported by the Deutsche Forschungsgemeinschaft under contract No. KR 1172/9-2 and D-wave Sys. Inc.

-
- * On leave from B. Verkin Institute for Low Temperature Physics and Engineering, National Academy of Sciences of the Ukraine, 310164 Kharkov, Ukraine.
- † Electronic address: owk@rz.uni-jena.de
- ‡ On leave from Department of Solid State Physics, Comenius University, SK-84248 Bratislava, Slovakia.
- ¹ A.J. Leggett, *Science* **296**, 861, (2002).
- ² D.V. Averin and K.K. Likharev, in *Mesoscopic Phenomena in Solids*, edited by B.L. Altshuler, P.A. Lee, and R.A. Webb (Elsevier, Amsterdam, 1991), p. 173, and M. Tinkham, in *Introduction to superconductivity* (McGraw-Hill, New York, 1996), 2nd ed., Chap. 7.
- ³ P. Joyez, P. Lafarge, A. Filipe, D. Esteve, and M. Devoret, *Phys. Rev. Lett.* **72**, 2458 (1994).
- ⁴ T.M. Eiles and J.M. Martinis, *Phys. Rev. B* **50**, 627 (1994).
- ⁵ D.J. Flees, S. Han, and J.E. Lukens, *Phys. Rev. Lett.* **78**, 4817 (1997).
- ⁶ Y. Nakamura, C.D. Chen, and J.S. Tsai, *Phys. Rev. Lett.* **79**, 2328 (1997).
- ⁷ Y. Nakamura, Yu.A. Pashkin, and J.S. Tsai, *Phys. Rev. Lett.* **87**, 246601 (2001).
- ⁸ D. Vion, A. Aasime, A. Cottet, P. Joyez, H. Pothier, C. Urbina, D. Esteve, and M.H. Devoret, *Science* **296**, 886 (2002). Especially, the authors report on band gap spectroscopy of a similar superconducting circuit (“quantro-

- nium”) that was performed by measuring the switching probabilities of interband transitions.
- ⁹ J.R. Friedman and D.V. Averin, *Phys. Rev. Lett.* **88**, 050403 (2002).
- ¹⁰ A.B. Zorin, *Physica C* **368**, 284 (2002).
- ¹¹ W. Krech, M. Grajcar, D. Born, I. Zhilyaev, Th. Wagner, E. Il’ichev, and Ya. Greenberg, *Phys. Lett. A* **303**, 352 (2002).
- ¹² R. Rifkin and B.S. Deaver, *Phys. Rev. B* **13**, 3894 (1976).
- ¹³ The band index can be related simply to the number m of excess pairs on the island in the pure charge states ($\epsilon_J \rightarrow 0$; $0 < n_g < 1$). Within the two-band model, this procedure leads to $|m=0\rangle$ (lower state) and $|m=1\rangle$ (upper state), respectively (cf. Ref. 7).
- ¹⁴ E. Il’ichev, V. Zakosarenko, L. Fritsch, R. Stolz, H.E. Hoenig, H.-G. Meyer, M. Götz, A.B. Zorin, V.V. Khanin, A.B. Pavolotsky, and J. Niemeyer, *Rev. Sci. Instr.* **72**, 1882 (2001).
- ¹⁵ Measurements of ground band properties of a similar system were reported by M. Götz, S.A. Bogolovsky, and A.B. Zorin, in *Tagungsband 8th Statusseminar BMBF Feb. 13-14, 2003, Garmisch-Partenkirchen* (VDI Technologiezentrum, Düsseldorf, 2003), p. 50.